

Go Music Receiver

Go Music Multi-frequency Receiver

The OSL Go Music Receiver is designed to be small enough to fit in your instrument case or travel bags with ease. Built for musicians, the setup is quick and easy with the antenna's prefixed onto the system. The Go Music Receiver is powered by a standard 12V power supply or for even quicker and more portable setups can be power by AA batteries. It offers 16 channels of simultaneous use and syncs with the Go Music transmitters via infrared. The receiver is perfect for musicians who demand highest



Technical Specifications

Diversity Principle	True Diversity
Operating Channels	16 Channels Simultaneous Use
Frequency Selection	Auto Selection with IR Sync
Frequency Bands	C: 734 - 776 MHz; GB: 606 - 648 MHz; E: 823 - 865 MHz; D: 780 - 822 MHz
Frequency Range	20 Hz - 20 kHz
Modulation	Wideband FM
Power Supply	DC12V-18V / 500mA or 2 AA batteries, 1.5 V

Dimensions

Height	110 mm
Width	130 mm
Depth	50 mm
Net Weight	850 gms